

**INSTRUCTIONS FOR SCANNING THE NEW 3ABN FREQUENCY
STRONG SRT 3500**

PLEASE BE AWARE – THESE INSTRUCTIONS WILL BE INEFFECTIVE IF YOU HAVE PERFORMED A FACTORY RESET
Please follow the steps as listed. Do not change anything unless specified. Please do not perform a factory reset.
Christian Satellite is not liable for any damage or loss of programming that may be incurred by following these instructions.

STEP 1 - Scanning the frequency 12546 for the new location of 3ABN

- A.** Press the **MENU** button and scroll **LEFT** or **RIGHT** by using the **VOL- VOL+** button and highlight **SETUP** and press the **OK** button.
- B.** Next highlight **SATELLITE** and press the **OK** button.
- C.** Next highlight **SCAN TRANSPONDER** and press the **OK** button. The receiver may request a password. Enter **9402** by using the numbers on the remote and if that does not work try **0000**.
- D.** Next highlight **SATELLITE** and press the **OK** button and a window will pop up.
- E.** Next in the list scroll **UP** or **DOWN** and highlight **OPTUS B3 152.0 E** press the **OK** button.
- F.** Next scroll **DOWN** and highlight **FREQ (MHz)** and slowly enter **12546** by using the numbers on the remote.
- G.** Next scroll **DOWN** and highlight **SR (KsPS)** and slowly enter **22500** by using the numbers on the remote.
- H.** Next scroll **DOWN** and highlight **LNB SELECT** and press the **VOL –** or **VOL +** button and select **LNB 4**.
- I.** Next scroll **DOWN** and highlight **LNB POLARISATION** and press the **VOL –** or **VOL +** button and select **V**.
- J.** Next scroll **DOWN** and highlight **SCAN TYPE** and press the **VOL –** or **VOL +** button and select **FTA**.
- K.** Next scroll **DOWN** and highlight **TV / RADIO** and select **DATA**
- L.** Next scroll **DOWN** and highlight **OK TO START SCAN** please note before you press the **OK** button please check that the **SIGNAL QUALITY** bar at the bottom of the screen is more than **0%** and then press the **OK** button and the receiver will begin searching for the channels. If the **SIGNAL QUALITY** bar at the bottom of the screen is not more than **0%** you may be using an **AUSTAR** or **FOXTEL** dish so you will need to change the **LNB SELECT** in **STEP 1** to **LNB 3** and then press the **OK** button.
- M.** When the receiver is finished scanning a **"TUNING" NO SERVICE(S) ADDED** window will appear. Press the **OK** button and the receiver will exit to the main menu.
- N.** Next scroll **UP** and highlight **SATELLITE SCAN** and press the **OK** button. The receiver may request a password. Enter **9402** by using the numbers on the remote and if that does not work try **0000**.
- O.** Next highlight **SATELLITE** and press the **OK** button and a window will pop up.
- P.** Next in the list scroll **UP** or **DOWN** and highlight **OPTUS B3 152.0 E** press the **OK** button.
- Q.** Next scroll **DOWN** and highlight **XPDR SELECT** and press **LEFT** or **RIGHT** and select **12546 / 22500 /V**.
- R.** Next scroll **DOWN** and highlight **SEARCH TYPE** and press **LEFT** or **RIGHT** and select **TP SEARCH**.
- S.** Next scroll to **OK TO START SCAN** and press the **OK** button.
- T.** When the receiver is finished scanning a **"TUNING"** window will appear. Press the **OK** button and the receiver will exit to the main menu.

STEP 2 – Organising channels

- A.** To move your favorite channels press the **CHANNEL** buttons and highlight the channel that you would like to move and then press the **GREEN** button on the remote and the channel will highlight in green
- B.** Next scroll **UP** or **DOWN** and highlight where you would like the channel to appear in the list and then press the **GREEN** button. Continue with step **A** and **B** with all the channels that you would like to move.
- C.** Once you are finished press the **EXIT** button on the remote and the receiver will save the changes and exit to the main menu.
- D.** Next press the **EXIT** button **3** times and the receiver will exit out of the main menu. You have finished!!